

BV13 & BV17 Battery Tooling



The BV13, for blind fasteners, and the BV17, for HuckBolts, deliver durable performance anywhere along the production line or in the field for towers, solar racks and more.

Designed by Makita® to fit their latest 40 V battery technology, the BV13 and BV17 can install leading Huck Fasteners without being tethered to pneumatic or hydraulic power.



Kit includes:

- > Tool > Two 4.0 Ah Batteries
- > Charger > Carrying Case

Specifications:

Capacity:	5/16" (8.0 mm) - 1/2" (12.8 mm)
Stroke Length:	1.77" (45 mm)
Pulling Force:	BV13 - up to 13,000 lbf (56 kN)
	BV17 - up to 17,000 lbf (76 kN)
Weight:	14.3 lbs tool only
	16.5 lbs with 4.0 Ah Battery
	17.4 lbs with 5.0 Ah Battery
Battery Pack:	40 V / Li-ion/4.0 Ah
	40 V / Li-ion/5.0 Ah*
Recharge Time:	4.0 Ah Battery - 28 minutes
	5.0 Ah Battery* - 40 minutes

Features:

- ✓ Electronically adjustable pull force control
- ✓ Designed for Huck installation noses
- √ Removable side handle for ease of use
- √ High pull force enables installation of Huck structural blind rivets and two-piece fasteners up to 1/2" in diameter





Data and Dimensions

BV13/BV17

NOSEPIECE PART NUMBER	FASTENER
99BOM-10-IRBU	5/16" BOM®
99BOM-12-FRBU	Self Releasing, 3/8" BOM
99C6L-10-IRBU	5/16" C6L/C120L
99C6L-12-IRBU	3/8" C6L/C120L
99MGL-12-IRBU	3/8" MagnaLok®
99MGL-M11-IRBU	11 mm MagnaLok
99MGC-10-IRBU	5/16" MagnaGrip®
99MGC-12-IRBU	3/8" MagnaGrip
99BMT-16-IRBV	1/2" BOMTail™**
99BT-16-IRBV	1/2" BobTail®
99BT-16-CRBV	Cutter 1/2" BobTail
99BT-M12-IRBV-X	12 mm BobTail
99BT-M12-CRBV	Cutter 12mm BobTail
99BT-M14-IRBV-X	14 mm BobTail**
99BT-M14-CRBV	Cutter 14mm BobTail**

^{**} Use only with BV17

PART NO.

Tool Packages & Accessories

DESCRIPTION

BV13-177-K0	13,000 lbf Battery Tool and Carrying Case
BV13-177-K2	13,000 lbf Battery Tool, Two 4.0 Ah Batteries, One Charger, and Carrying Case
BV17-177-K0	17,000 lbf Battery Tool and Carrying Case
BV17-177-K2	17,000 lbf Battery Tool, Two 4.0 Ah Batteries, One Charger, and Carrying Case

MB-4040 Extra Battery, 40 V, 4.0 Ah MB-4050 Extra Battery, 40 V, 5.0 Ah MCH-40-120 Battery Charger, 40 V, 120 V input

> $\hbox{Disclaimer: The information contained in this publication is only for general guidance, and is not intended to } \\$ create any warranty, express, implied, or statutory; all warranties are contained only in HFS's written quotations, $acknowledgments, and/or\ purchase\ orders.\ It\ is\ recommended\ that\ the\ user\ secure\ specific,\ up-to-date\ data$ and information regarding each application and/or use of such products.













